



Mobile solution for wireless surveillance

Piccolo® Mobile alarm solution is a flexible GSM alarm unit with a built-in battery which supplies *Piccolo® Mobile* for approx. three days without charging. The suitcase contains:

- 1 *Piccolo® Light*
- 2 PIR-spots
- 1 inSpot (for wired alarm sensor)
- 1 remote control (for connecting/disconnecting the unit)
- 1 battery, 12V, 3,2 Ah incl. adapter

Alarms are transmitted as SMS, voice message or e-mail to maximum 9 predefined phone numbers. A built-in siren can, like the relays, be activated by alarm.

The alarm unit is especially applicable for temporary protection of construction sites and exhibitions. The system

Piccolo® Mobile alarm solution is easy to install. The unit contains a GSM-modem, a built-in siren, remotely-controllable relays, and an alarm receiver. All you need extra is a SIM-card from a phone company. A CD with installation software for PC and an operating manual are enclosed.

Piccolo® Mobile alarm unit has a built-in clock which enables activation and supervision at certain times. By sabotage an alarm will be sent immediately. If you insert a backup battery you will receive a message in case of power failure.

Facts:

Profort A/S is a Danish engineering company. We have 10 years experience of developing electronics and applications with wireless technology as speciality. Profort's products are exported to many European countries.

Piccolo® is developed and produced in Denmark.

Piccolo® Mobile alarm unit





combiSpot
with seismic and magnetic sensor for e.g. paintings.



infraSpot
with infrared sensor for e.g. sculptures and paintings



ultraSpot
with ultra sound for show-cases and small rooms



buzzerSpot
seismic and magnetic sensor with acoustic signal caused by vibration, e.g. for paintings



inSpot
alarm transmission from other wired equipment





PIRSpot
for surveillance of rooms



Personal alarm
with 2 alarm buttons



Remote control
connecting/disconnecting the unit.



Function:


Piccolo® Light sends alarm messages to telephones, PC or alarm centrals as SMS, voice messages or e-mails. The alarms are sent by activation of sensors and inputs, by sabotage, power failure etc.

By calling or sending a message to *Piccolo® Light* it is possible to activate or deactivate the relay-outputs. The relays can also be activated as a function of the status on the inputs.

Programming/setting up *Piccolo® Light* can be done from display/keys, a mobile phone by SMS, via PC locally or remotely by using the PC-setup software.

Specifications:

Weight:	approx. 10 kg
Power supply:	230VAC
Siren:	Built-in
Wireless:	Max. 60 wireless units
Outputs:	8 relay-outputs, max. 230VAC, 0,5A max. 35VDC, 2A
Inputs:	8 inputs. Alarm on NC and NO. Incl. pulse counter, max 20 Hz. 2 inputs. Analog measuring, 0-5V
Sabotage:	Alarm on opening the unit.
Power failure:	Approx. 3 days battery lifetime. An alarm will be sent when the battery is low.
Programming:	Via serial COM on a PC, a SMS from a PC or a mobile phone
Antenna:	Built-in. External antenna is available as extra equipment
Receiver list:	Up to 9 phone numbers
Voice messages:	in total 40 sec.
Temperature:	±20°C to + 55°C



Profort as
Gunnar Clausens Vej 3
DK - 8260 Viby J
Tlf.: +4570233600
info@profort.com
www.profort.com

